

TENSIOTRON[®] TS 621

Precision Strain Gauge Measurement Amplifier



The **TENSIOTRON[®] TS 621** electronic strain gauge amplifier combines the highest quality power and signal conditioning capabilities suitable for use with most strain gauge-based sensors, esp. tension measurement.

Best temperature stability, long-term stability and high accuracy are guaranteed by using modern technology.

The **TS 621** delivers superb performance features such as galvanic isolation, removable terminal block for the sensor connections, multiple options and high quality.

Special features:

- Great noise immunity and service reliability for use in rough industrial operation
- Direct input power supply of 24V DC, reverse-polarity protected, providing
 - wide operating input power supply of 19-36V DC, LED indicates power-on status
 - integrated DC-DC converter for galvanic isolation between power supply and measuring circuit (very important to avoid ground loops in combination with secondary electronics)
- Provides a well-regulated power supply for sensor excitation, balanced to ground
- Coarse and fine adjustments for zero and amplification setting
- Screw terminal for power and outputs
- Removable screw terminal plug for the sensor connections
 - available accessory: adapter plug 2/1 (parallel connection of 2 sensors directly at amplifier input)
- Standard: voltage output 0-10V, bipolar

Optional outputs available:

- Option **D** → additional damped voltage output, selectable cut-off frequency 0,5 / 5 / 10 / 20Hz
- Option **A** → additional current output, selectable 0-20 / 4-20mA, unipolar or bipolar
- Option **X** → additional voltage output, selectable amplification factor 2x, 3x, 4x, 5x

Technical Data TS 621

| Designation | | Tensiotron® TS 621 |
|---|----------------------------------|---|
| Design | | DIN-rail housing for convenient snap-in installation |
| Accuracy class | | 0,1 |
| Sensors to be connected: - strain gauge, full bridge | Ω | admissible connection impedance ≥ 150 |
| Bridge excitation voltage (referenced to ground) | V DC | $10 \pm 0,5 \%$ |
| Nominal gain G_{nom} | | 667 |
| Nominal measuring range U_{sig} | mV | ± 15 |
| Calibration range referenced to G_{nom} | % | 38 to 100 to 580 |
| Adjustment range zero @ G_{nom} - fine approx. - coarse approx. | % ¹ % ¹ | ± 20 ± 60 |
| Input impedance | Ω | 10^{10} |
| Cut-off frequency (- 3 dB) | Hz | approx. 70 |
| Standard output - voltage output V_{out} (@ $G_{nom} \cdot U_{sig}$) | V | 0 to ± 10 , max. 10 mA |
| OPTION additional output: - D damped voltage output V_{dout} Bessel low-pass-filter 5 th order (configuration via DIP switch) | V Hz | 0 to ± 10 , max. 10 mA $f_c = 0,5 / 5 / 10 / 15$ |
| - A current output ($f_c = 500$ Hz) - bipolar - unipolar - unipolar (configuration via DIP switch) | mA mA mA | 0 to ± 20 , admissible load 0 to 500 Ω 0 to + 20, admissible load 0 to 500 Ω 4 to + 20, admissible load 0 to 500 Ω |
| - X voltage output with selectable amplification factor X $V_{out}^* = X \cdot V_{out}$ ($f_c = 25$ Hz) voltage output V_{out}^* (configuration via DIP switch) | V V | $V_{out}^* = 2 / 3 / 4 / 5 \cdot V_{out}$ 0 to ± 10 , max. 10 mA |
| Nominal temperature range | $^{\circ}$ C | 0 to + 60 |
| Operation temperature range | $^{\circ}$ C | 0 to + 60 |
| Storage temperature range | $^{\circ}$ C | -25 to + 75 |

| | | |
|--|----------------------|--|
| Temperature influence per 10 °C - on zero at amplifier output - on calibration | mV % ¹ | < 10 (@ G _{nom}) < 0,05 |
| Supply voltage Power consumption | V DC W | 19 to 36 max. 3 integrated DC-DC converter for galvanic isolation between supply voltage and measurement circuit |
| Amplifier connection | | screw terminals for flexible cable 0,2 to 2,5 mm ² |
| Sensor connection | | plug with screw terminals for flexible cable 0,08 to 1,5 mm ² |
| Dimensions (L x W x H) | mm | 80 x 25 x 95 |
| Weight | g | approx. 100 |
| Installation | | Snap-in installation on DIN-EN mounting rails |

¹ of final value

Explanation of grammalogue:

f_c ⇒ Cut-off frequency

G_{nom} ⇒ Nominal gain amplification factor

U_{sig} ⇒ Input voltage

V_{out} ⇒ Voltage at standard output

V_{out}* ⇒ Voltage at optional output with select.

V_{dout} ⇒ Voltage at optional damped output

*Technical execution subject to change without prior notice
Reproduction - in whole, in part or in translation - is prohibited*